




IB-ACH-01 (Interface Amplifier)

SPECIFICATIONS

- Designed to interface with the ACH-01 Accelerometer
- 10X Amplification
- Impedance Buffered
- BNC Output Connector

The **IB-ACH-01 Amplifier Box** is a low cost interface amplifier developed by MEAS. The IB-ACH-01 is designed to mate directly to the connector supplied with the ACH-01-03 assembly. An adapter is required to interface the two components for use with either the ACH-01-02 or the ACH-01-04 because of the different cables.

DIMENSIONS



FEATURES

- Gain 10X
- Low Frequency Filter -3dB @ 2Hz Fixed
- High Frequency Filter +3dB @ 30kHz Fixed
- Power Supply – One 9-Volt Battery
- Input Interface – FET for IB-ACH-01
- Supply Current 4.0 mA
- Battery Life 80 Hours
- Low Battery Cutoff 7.2V
- Output Impedance 100 Ohm
- Output Connector BNC

APPLICATIONS

- Signal Amplification Box for ACH-01 Series Accelerometer

PERFORMANCE SPECIFICATIONS

Frequency Response:	Amplitude: Fixed 10 x Gain (90 mv/g Typical w/ ACH-01) $\pm 3\%$ from 2 Hz to 30 kHz
	Phase: $<+1.5\%$ @10Hz $<-5.0\%$ @20kHz
Output Impedance:	Inherent Noise: (2Hz to 30kHz): $<2mV_{pk-pk}$
Current Draw:	AC Coupled – 1 μ F (w/o Battery Check LED)
	Typical: 4.0 ma
	Maximum: 7.6 ma
Cut-off Voltage:	@7.2V
Battery Life:	(w/o Battery Check LED): 80 hrs Typical (alkaline)
Rise Time:	13V/ μ s Typical
Maximum Output:	9V _{pk-pk}

BATTERY INSTALLATION

To replace or install battery, remove the housing cover by loosening the four screws on the box. Lift the lid slowly. Be sure not to tear the wires between the lid and the main housing. Replace the battery and reattach the lid by tightening the screws. The IB-ACH-01 is NOT shipped with a battery.

OPERATION

Prior to operation check the Battery Low indicator LED by pushing the switch to the Battery Check (Batt. Chk.) Position. If the LED does not light replace the battery. The switch must be in the ON position for the amplifier box to function.

After checking the battery check the connection between the ACH-01 and the amplifier for correct orientation (see Figure 1 and the ACH-01 specification sheet). Depending on the ACH-01 configuration it may be necessary to use the supplied female-to-female cable for connection to the IB-ACH-01 amplifier.

ORDERING INFORMATION

Description	Part Number
IB-ACH-01	1003058

NORTH AMERICA

Measurement Specialties, Inc.,
a TE Connectivity Company
Vibration Design Center
32 Journey - Suite 150
Aliso Viejo, CA 92656
United States USA
Tel: 1-949-716-0877
Fax: 1-949-916-5677
t&m@meas-spec.com

EUROPE

MEAS France SAS
a TE Connectivity Company
26 Rue des Dames
78340 Les Clayes-Sous-Bois, France
Tel: +33 (0) 130 79 33 00
Fax: +33 (0) 134 81 03 59
cs.lcsb@meas-spec.com

ASIA

Measurement Specialties (China), Ltd.,
a TE Connectivity Company
No. 26 Langshan Road
Shenzhen High-Tech Park (North)
Nanshan District, Shenzhen 518057 China
Tel: +86 755 3330 5088
Fax: +86 755 3330 5099
pfg.cs.asia@meas-spec.com

TE.com/sensorsolutions

Measurement Specialties, Inc., a TE Connectivity company.

Measurement Specialties, TE Connectivity, TE Connectivity (logo) and EVERY CONNECTION COUNTS are trademarks. All other logos, products and/or company names referred to herein might be trademarks of their respective owners.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, TE Connectivity makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. TE Connectivity's obligations shall only be as set forth in TE Connectivity's Standard Terms and Conditions of Sale for this product and in no case will TE Connectivity be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of TE Connectivity products should make their own evaluation to determine the suitability of each such product for the specific application.

© 2015 TE Connectivity Ltd. family of companies All Rights Reserved.